

ROAM XL REMOTE

Add professional, licence-free remote control to projects of any size with this long-range remote.

KEY BENEFITS

- Compatibility with Hunter X-Core™, X2™, Pro-C™, HPC, ICC2, HCC, ACC2, and legacy ACC and I-Core™ Controllers to enable remote management for projects of any size
- Manually start individual stations or programs for quick maintenance checks and troubleshooting
- 128 programmable addresses available prevents cross-communication between multiple remotes within close proximity of each other
- Programmable run times from 1 to 90 minutes, which will not overwrite regular automatic programming
- Manual operation up to 240 stations provides flexibility for larger projects
- Rugged and water-resistant transmitter includes a large LCD display with simple push-button operation and a battery-life indicator

OPERATING SPECIFICATIONS

- Range: 3 km (line of sight) from transmitter to receiver
- Transmitter power source: 4 x AAA batteries included
- Receiver power source: 24 VAC, 0.010 A
- System operating frequency: 27 MHz
- SmartPort™ installation: Maximum 15 m from controller
- FCC approved (not available in EU and some other countries, check local regulations)
- Warranty period: 3 years



ROAM XL Transmitter and Receiver
(without antenna)
Height: 16 cm
Width: 8 cm
Depth: 3 cm

ROAM XL	
Model	Description
ROAMXL-KIT	Transmitter, receiver, SmartPort Wiring Harness, 4 AAA batteries and plastic carrying case included
ROAMXL-R	Receiver unit (SmartPort Wiring Harness included)
ROAMXL-TR	Handheld transmitter and 4 AAA batteries included

USER-INSTALLED OPTIONS	
Model	Description
258200	Wall-mount bracket for SmartPort
ROAM-WH	SmartPort Wiring Harness (length: 1.8 m)
ROAM-SCWH	Shielded SmartPort Wiring Harness (length: 7.6 m)
ROAMXL-EXT	ROAM XL Antenna Extension Kit (7.6 m cable and mounting hardware included)



SmartPort
Hunter remotes require the installation of a SmartPort Wiring Harness. The SmartPort is a connector that is wired to the terminals on the controller, and allows quick connection to any Hunter receiver.



Wall-Mount Bracket for SmartPort
P/N 258200